



6KVA 400 VOLTS TO 208 VOLTS THREE PHASE AUTOTRANSFORMER

\$1,647.60 CAD

Three Phase Autotransformer with a capacity of 6kVA, transforming 400Y Volts to 208Y Volts

SKU: RC6G1-B

Categories: [Autotransformers](#)

SCHEMATIC/DIAGRAM AND DIMENSION PICTURES



Three Phase Autotransformer with a capacity of 6kVA, transforming 400Y Volts to 208Y Volts



PRODUCT SPECIFICATIONS

Weight	20 lbs
Phases	3
kVA	6
Connection	3PhA-NT-1
Primary Voltage	400
Primary Max Current	8.7A
Primary Markings	H1-H2-H3
Primary Terminals	Terminal Blocks
Secondary Voltage	208
Secondary Max Current	16.7A
Secondary Markings	X1-X2-X3
Secondary Terminals	Terminal Blocks
Primary Taps	N/A
Conductor Material	Copper
Insulation Class	180°C (Class F)
BIL (Insulation) Level	10kV
Efficiency (@35% Load) %	N/A
Impedance Range	1.5 – 3.5%
Sound (db)	40
Enclosure Type	NEMA 1
Enclosure Size	E1-1
Finish/Colour	Polyester Powder Coat – ANSI/ASA 61 Grey
Standards & Certifications	CSA Certified File No. LR34493, UL Listed File No. E108255, ISO 9001:2015 Registered



OFFICIAL QUOTE
6KVA 400 VOLTS TO 208 VOLTS
THREE PHASE AUTOTRANSFORMER



Country/Manufacturer	Canada/RPM
----------------------	----------------------------