




100VA 600 VOLTS TO 12/24 VOLTS
SINGLE PHASE CONTROL
TRANSFORMER



100VA 600 VOLTS TO 12/24 VOLTS SINGLE PHASE CONTROL TRANSFORMER

\$131.04 CAD



Single Phase Control Transformer with a capacity of 100VA, transforming 600 Volts to 12/24 Volts

SKU: CS100J-Z

Categories: [Control Transformers](#)

SCHEMATIC/DIAGRAM AND DIMENSION PICTURES

VA	Overall Dimensions (Inches)				
Rating	A	B	C	Mounting Centre D.A.	F
25	3	3	2.5	2.5	3.33
40	3	3	2.5	2.5	3.33
100	4	4	2.5	3	3.75
150	3.75	4.25	3.33	3.25	3.5
200	3.75	4.5	3.33	3.25	3.5
250	3.75	5	3.33	3.25	3.5
350	4.5	5	3.75	3.75	4.75
500	5.25	5	4.38	4.5	5.75
750	5.25	5.5	4.38	4.5	5.75
1000	5.25	6.5	4.38	4.5	5.75
1500	6.75	7.25	5.63	5	6.75
2000	7.5	7.5	6.25	6	6.25
3000	7.5	8.75	6.25	6	6.5
5000	9	10	8	7	8



Single Phase Control Transformer with a capacity of 100VA, transforming 600 Volts to 12/24 Volts



PRODUCT SPECIFICATIONS

Weight	5 lbs
Phases	1
Connection	1Ph-CT-SD-SD
Primary Voltage	600
Primary Max Current	0.17A
Primary Markings	H1-H2
Primary Terminals	Terminals
Secondary Voltage	12/24
Secondary Max Current	8.33A
Secondary Markings	X1-X2-X3-X4
Secondary Terminals	Terminals
Primary Taps	N/A
Conductor Material	Copper
Temperatue Rise	80°C
Insuation Class	130°C (Class B)
BIL (Insulation) Level	10kV
Efficiency (@35% Load) %	N/A
Impedance Range	5.0 – 7.0%
Sound (db)	40
Enclosure Type	Core & Coil
Enclosure Size	See Core & Coil Chart
Finish/Colour	N/A
Standards & Certifications	CSA Certified File No. LR34493, UL Listed File No. E110286, ISO 9001:2015 Registered



OFFICIAL QUOTE

100VA 600 VOLTS TO 12/24 VOLTS
SINGLE PHASE CONTROL
TRANSFORMER



VA	
Country/Manufacturer	Canada/RPM