



## 150VA 600 VOLTS TO 120 VOLTS SINGLE PHASE CONTROL TRANSFORMER

**\$182.00 CAD**

Single Phase Control Transformer with a capacity of 150VA, transforming 600 Volts to 120 Volts

SKU: CE150J-A

Categories: [Control Transformers](#)

### SCHEMATIC/DIAGRAM AND DIMENSION PICTURES

| Control Transformer Dimensions (Table of Dimensions) |                    |       |      |                              |       |  |
|--|--------------------|-------|------|------------------------------|-------|--|
| VA Rating  | Overall Dimensions |       |      |                              |       |  |
|  | A                  | B     | C    | Mounting Dimensions<br>Ø x L |       |  |
| 25   | 3                  | 6     | 3.5  | 1.375                        | 4.375 |  |
| 50   | 3                  | 6     | 3.5  | 1.375                        | 4.375 |  |
| 100  | 3                  | 6     | 3.5  | 1.375                        | 4.375 |  |
| 150  | 3.5                | 6.658 | 3.13 | 3.25                         | 5     |  |
| 200  | 3.5                | 6.658 | 3.13 | 3.25                         | 5     |  |
| 250  | 3.5                | 6.658 | 3.13 | 3.25                         | 5     |  |
| 350  | 4.125              | 6.5   | 3.75 | 3.75                         | 7.875 |  |
| 500  | 4.875              | 7     | 4.38 | 4.5                          | 5.5   |  |
| 750  | 4.875              | 7     | 4.38 | 4.5                          | 5.5   |  |
| 1000   | 4.875              | 7     | 4.38 | 4.5                          | 5.5   |  |
| 1500   | 5.625              | 9     | 5.63 | 5                            | 7.25  |  |
| 2000   | 6.875              | 9.25  | 6.25 | 6                            | 8     |  |
| 3000   | 6.875              | 9.25  | 6.25 | 6                            | 8     |  |
| 5000   | 8                  | 10.5  | 9.5  | 6                            | 9     |  |



Single Phase Control Transformer with a capacity of 150VA, transforming 600 Volts to 120 Volts



**OFFICIAL QUOTE**  
**150VA 600 VOLTS TO 120 VOLTS**  
**SINGLE PHASE CONTROL**  
**TRANSFORMER**





## PRODUCT SPECIFICATIONS

|                            |  |
|----------------------------|--|
| Weight                     | 6 lbs  |
| Phases                     | <a href="#">1</a>  |
| Connection                 | <a href="#">1Ph-CT-SS-SU</a>   |
| Primary Voltage            | <a href="#">600</a>  |
| Primary Max Current        | <a href="#">0.25A</a>  |
| Primary Markings           | <a href="#">H1-H2</a>  |
| Primary Terminals          | <a href="#">Leads</a>  |
| Secondary Voltage          | <a href="#">120</a>  |
| Secondary Max Current      | <a href="#">1.25A</a>  |
| Secondary Markings         | <a href="#">X1-X2</a>  |
| Secondary Terminals        | <a href="#">Leads</a>  |
| Primary Taps               | <a href="#">N/A</a>  |
| Conductor Material         | <a href="#">Copper</a>   |
| Temperature Rise           | <a href="#">80°C</a>   |
| Insulation Class           | <a href="#">130°C (Class B)</a>  |
| BIL (Insulation) Level     | <a href="#">10kV</a>   |
| Efficiency (@35% Load) %   | <a href="#">N/A</a>  |
| Impedance Range            | <a href="#">5.0 – 7.0%</a>   |
| Sound (db)                 | <a href="#">40</a>   |
| Enclosure Type             | <a href="#">Type-1 Indoor</a>  |
| Enclosure Size             | <a href="#">See Enclosure Chart</a>  |
| Finish/Colour              | <a href="#">Semigloss – Black</a>  |
| Standards & Certifications | <a href="#">CSA Certified File No. LR34493, UL Listed File No. E110286, ISO 9001:2015 Registered</a> |



OFFICIAL QUOTE  
150VA 600 VOLTS TO 120 VOLTS  
SINGLE PHASE CONTROL  
TRANSFORMER



|                      |                            |
|----------------------|----------------------------|
| VA                   | <a href="#">150</a>        |
| Country/Manufacturer | <a href="#">Canada/RPM</a> |