

#### **OFFICIAL QUOTE**

### 2000VA 480 VOLTS TO 120/240 VOLTS SINGLE PHASE CONTROL TRANSFORMER





### 2000VA 480 VOLTS TO 120/240 VOLTS SINGLE PHASE CONTROL TRANSFORMER

\$669.76 CAD


Single Phase Control Transformer with a capacity of 2000VA, transforming 480 Volts to 120/240 Volts

**SKU:** CS2000H-K

**Categories:** Control Transformers

#### **SCHEMATIC/DIAGRAM AND DIMENSION PICTURES**





Single Phase Control Transformer with a capacity of 2000VA, transforming 480 Volts to 120/240 Volts



#### **OFFICIAL QUOTE**



# 2000VA 480 VOLTS TO 120/240 VOLTS SINGLE PHASE CONTROL TRANSFORMER

#### **PRODUCT SPECIFICATIONS**

Weight	70 lbs
Phases	1
Connection	1Ph-CT-SD-SD
Primary Voltage	480
Primary Max Current	4.17A
Primary Markings	H1-H2
Primary Terminals	<u>Terminals</u>
Secondary Voltage	120/240
Secondary Max Current	16.67A
Secondary Markings	<u>X1-X2-X3-X4</u>
Secondary Terminals	<u>Terminals</u>
Primary Taps	N/A
Conductor Material	Copper
Temperatue Rise	<u>115°C</u>
Insuation Class	180°C (Class F)
BIL (Insulation) Level	<u>10kV</u>
Efficiency (@35% Load) %	N/A
Impedance Range	<u>5.0 - 7.0%</u>
Sound (db)	40
Enclosure Type	Core & Coil
Enclosure Size	See Core & Coil Chart
Finish/Colour	N/A
Standards & Certifications	CSA Certified File No. LR34493, UL Listed File No. E110286, ISO 9001:2015 Registered



#### **OFFICIAL QUOTE**



# 2000VA 480 VOLTS TO 120/240 VOLTS SINGLE PHASE CONTROL TRANSFORMER

VA	
Country/Manufacturer	Canada/RPM