



2000VA 480 VOLTS TO 240/480 VOLTS SINGLE PHASE CONTROL TRANSFORMER

\$669.76 CAD

Single Phase Control Transformer with a capacity
of 2000VA, transforming 480 Volts to 240/480
Volts

SKU: CS2000H-L

Categories: [Control Transformers](#)

SCHEMATIC/DIAGRAM AND DIMENSION PICTURES

| Volts | Overall Dimensions | Mounting Dimensions |
|--------|--------------------|---------------------|
| Rating | A B C | D E F |
| 25 | 3 3 2.5 | 2.5 2.5 3.33 |
| 30 | 3 3 2.5 | 2.5 2.5 3.33 |
| 100 | 3 4 2.5 | 2.5 3 3.75 |
| 150 | 3.75 4.25 3.33 | 3.25 3.5 4.5 |
| 200 | 3.75 4.5 3.33 | 3.25 3.5 4.5 |
| 250 | 3.75 5 3.33 | 3.25 3.5 4.5 |
| 350 | 4.5 5 3.75 | 3.75 3.75 4.75 |
| 500 | 5.25 5 4.38 | 4.5 3.75 4.75 |
| 750 | 5.25 5.5 4.38 | 4.5 3.75 4.75 |
| 1000 | 5.25 6.5 4.38 | 4.5 3.75 4.75 |
| 1500 | 6.75 7.25 5.0 | 5 3.75 5.25 |
| 2000 | 7.5 7.5 6.25 | 6 4.5 5.25 |
| 3000 | 7.5 8.75 6.25 | 6 5.5 6.5 |
| 5000 | 9 10 8 | 7 7 8 |



Single Phase Control Transformer with a capacity of 2000VA, transforming 480 Volts to 240/480 Volts



PRODUCT SPECIFICATIONS

| | |
|----------------------------|--|
| Weight | 70 lbs |
| Phases | 1 |
| Connection | 1Ph-CT-SD-SD |
| Primary Voltage | 480 |
| Primary Max Current | 4.17A |
| Primary Markings | H1-H2 |
| Primary Terminals | Terminals |
| Secondary Voltage | 240/480 |
| Secondary Max Current | 8.33A |
| Secondary Markings | X1-X2-X3-X4 |
| Secondary Terminals | Terminals |
| Primary Taps | N/A |
| Conductor Material | Copper |
| Temperatue Rise | 115°C |
| Insuation Class | 180°C (Class F) |
| BIL (Insulation) Level | 10kV |
| Efficiency (@35% Load) % | N/A |
| Impedance Range | 5.0 – 7.0% |
| Sound (db) | 40 |
| Enclosure Type | Core & Coil |
| Enclosure Size | See Core & Coil Chart |
| Finish/Colour | N/A |
| Standards & Certifications | CSA Certified File No. LR34493, UL Listed File No. E110286, ISO 9001:2015 Registered |



OFFICIAL QUOTE

2000VA 480 VOLTS TO 240/480
VOLTS SINGLE PHASE CONTROL
TRANSFORMER



| | |
|----------------------|----------------------------|
| VA | |
| Country/Manufacturer | Canada/RPM |