

OFFICIAL QUOTE

350VA 600 VOLTS TO 120 VOLTS SINGLE PHASE CONTROL TRANSFORMER





350VA 600 VOLTS TO 120 VOLTS SINGLE PHASE CONTROL TRANSFORMER

\$209.30 CAD


Single Phase Control Transformer with a capacity of 350VA, transforming 600 Volts to 120 Volts

SKU: CS350J-A

Categories: Control Transformers

SCHEMATIC/DIAGRAM AND DIMENSION PICTURES





Single Phase Control Transformer with a capacity of 350VA, transforming 600 Volts to 120 Volts



OFFICIAL QUOTE



350VA 600 VOLTS TO 120 VOLTS SINGLE PHASE CONTROL TRANSFORMER

PRODUCT SPECIFICATIONS

| Weight | 12 lbs |
|----------------------------|--|
| Phases | 1 |
| Connection | 1Ph-CT-SS-SU |
| Primary Voltage | 600 |
| Primary Max Current | <u>0.58A</u> |
| Primary Markings | <u>H1-H2</u> |
| Primary Terminals | <u>Terminals</u> |
| Secondary Voltage | 120 |
| Secondary Max Current | 2.92A |
| Secondary Markings | <u>X1-X2</u> |
| Secondary Terminals | <u>Terminals</u> |
| Primary Taps | N/A |
| Conductor Material | Copper |
| Temperatue Rise | 80°C |
| Insuation Class | 130°C (Class B) |
| BIL (Insulation) Level | <u>10kV</u> |
| Efficiency (@35% Load) % | N/A |
| Impedance Range | <u>5.0 – 7.0%</u> |
| Sound (db) | 40 |
| Enclosure Type | Core & Coil |
| Enclosure Size | See Core & Coil Chart |
| Finish/Colour | N/A |
| Standards & Certifications | CSA Certified File No. LR34493, UL Listed File No. E110286, ISO 9001:2015 Registered |



OFFICIAL QUOTE



350VA 600 VOLTS TO 120 VOLTS SINGLE PHASE CONTROL TRANSFORMER

| VA | 350 |
|----------------------|------------|
| Country/Manufacturer | Canada/RPM |