

OFFICIAL QUOTE

500VA 120/240 VOLTS TO 12/24 VOLTS SINGLE PHASE CONTROL TRANSFORMER





500VA 120/240 VOLTS TO 12/24 VOLTS SINGLE PHASE CONTROL TRANSFORMER

\$373.10 CAD


Single Phase Control Transformer with a capacity of 500VA, transforming 120/240 Volts to 12/24 Volts

SKU: CE500K-Z

Categories: Control Transformers

SCHEMATIC/DIAGRAM AND DIMENSION PICTURES

Control 1	Transforme				s (inches)
VA	Overall Dimensions				
Rating	Α	В	С	Mounting Dimensions D x E	
25	3	6	3.5	1.375	4.375
50	3	6	3.5	1.375	4.375
100	3	6	3.5	1.375	4.375
150	3.5	6.658	3.13	3.25	5
200	3.5	6.658	3.13	3.25	5
250	3.5	6.658	3.13	3.25	5
350	4.125	6.5	3.75	3.75	7.875
500	4.875	7	4.38	4.5	5.5
750	4.875	7	4.38	4.5	5.5
1000	4.875	7	4.38	4.5	5.5
1500	5.625	9	5.63	5	7.25
2000	6.875	9.25	6.25	6	8
3000	6.875	9.25	6.25	6	8
5000	8	10.5	9.5	6	9



Single Phase Control Transformer with a capacity of 500VA, transforming 120/240 Volts to 12/24 Volts



OFFICIAL QUOTE



500VA 120/240 VOLTS TO 12/24 VOLTS SINGLE PHASE CONTROL TRANSFORMER

PRODUCT SPECIFICATIONS

Weight	5 lbs		
Phases	1		
Connection	1Ph-CT-DD-SD		
Primary Voltage	120/240		
Primary Max Current	4.17A		
Primary Markings	H1-H2-H3-H4		
Primary Terminals	Leads		
Secondary Voltage	12/24		
Secondary Max Current	41.67A		
Secondary Markings	<u>X1-X2-X3-X4</u>		
Secondary Terminals	Leads		
Primary Taps	N/A		
Conductor Material	Copper		
Temperatue Rise	115°C		
Insuation Class	180°C (Class F)		
BIL (Insulation) Level	10kV		
Efficiency (@35% Load) %	N/A		
Impedance Range	5.0 - 7.0%		
Sound (db)	40		
Enclosure Type	Type-1 Indoor		
Enclosure Size	See Enclosure Chart		
Finish/Colour	Semigloss - Black		
Standards & Certifications	CSA Certified File No. LR34493, UL Listed File No. E110286, ISO 9001:2015 Registered		



OFFICIAL QUOTE



500VA 120/240 VOLTS TO 12/24 VOLTS SINGLE PHASE CONTROL TRANSFORMER

VA	
Country/Manufacturer	Canada/RPM