

OFFICIAL QUOTE

500VA 600 VOLTS TO 120 VOLTS SINGLE PHASE CONTROL TRANSFORMER





500VA 600 VOLTS TO 120 VOLTS SINGLE PHASE CONTROL TRANSFORMER

\$273.00 CAD


Single Phase Control Transformer with a capacity of 500VA, transforming 600 Volts to 120 Volts

SKU: CS500J-A

Categories: Control Transformers

SCHEMATIC/DIAGRAM AND DIMENSION PICTURES





Single Phase Control Transformer with a capacity of 500VA, transforming 600 Volts to 120 Volts



OFFICIAL QUOTE

500VA 600 VOLTS TO 120 VOLTS SINGLE PHASE CONTROL TRANSFORMER

PRODUCT SPECIFICATIONS

| PRODUCT SPECIFICATIONS | |
|----------------------------|--|
| Weight | 14 lbs |
| Phases | 1 |
| Connection | 1Ph-CT-SS-SU |
| Primary Voltage | 600 |
| Primary Max Current | 0.83A |
| Primary Markings | H1-H2 |
| Primary Terminals | <u>Terminals</u> |
| Secondary Voltage | 120 |
| Secondary Max Current | 4.17A |
| Secondary Markings | <u>X1-X2</u> |
| Secondary Terminals | <u>Terminals</u> |
| Primary Taps | N/A |
| Conductor Material | <u>Copper</u> |
| Temperatue Rise | 115°C |
| Insuation Class | 180°C (Class F) |
| BIL (Insulation) Level | 10kV |
| Efficiency (@35% Load) % | N/A |
| Impedance Range | <u>5.0 - 7.0%</u> |
| Sound (db) | 40 |
| Enclosure Type | Core & Coil |
| Enclosure Size | See Core & Coil Chart |
| Finish/Colour | N/A |
| Standards & Certifications | CSA Certified File No. LR34493, UL Listed File No. E110286, ISO 9001:2015 Registered |



OFFICIAL QUOTE



500VA 600 VOLTS TO 120 VOLTS SINGLE PHASE CONTROL TRANSFORMER

| VA | |
|----------------------|-------------------|
| Country/Manufacturer | <u>Canada/RPM</u> |