

OFFICIAL QUOTE

500VA 600 VOLTS TO 120 VOLTS SINGLE PHASE CONTROL TRANSFORMER





500VA 600 VOLTS TO 120 VOLTS SINGLE PHASE CONTROL TRANSFORMER

\$273.00 CAD


Single Phase Control Transformer with a capacity of 500VA, transforming 600 Volts to 120 Volts

SKU: CS500J-A

Categories: Control Transformers

SCHEMATIC/DIAGRAM AND DIMENSION PICTURES





Single Phase Control Transformer with a capacity of 500VA, transforming 600 Volts to 120 Volts



OFFICIAL QUOTE



500VA 600 VOLTS TO 120 VOLTS SINGLE PHASE CONTROL TRANSFORMER

PRODUCT SPECIFICATIONS

PRODUCT SPECIFICATIONS	
Weight	14 lbs
Phases	1
Connection	1Ph-CT-SS-SU
Primary Voltage	600
Primary Max Current	0.83A
Primary Markings	H1-H2
Primary Terminals	<u>Terminals</u>
Secondary Voltage	120
Secondary Max Current	4.17A
Secondary Markings	<u>X1-X2</u>
Secondary Terminals	<u>Terminals</u>
Primary Taps	N/A
Conductor Material	<u>Copper</u>
Temperatue Rise	115°C
Insuation Class	180°C (Class F)
BIL (Insulation) Level	10kV
Efficiency (@35% Load) %	N/A
Impedance Range	<u>5.0 - 7.0%</u>
Sound (db)	40
Enclosure Type	Core & Coil
Enclosure Size	See Core & Coil Chart
Finish/Colour	N/A
Standards & Certifications	CSA Certified File No. LR34493, UL Listed File No. E110286, ISO 9001:2015 Registered



OFFICIAL QUOTE



500VA 600 VOLTS TO 120 VOLTS SINGLE PHASE CONTROL TRANSFORMER

VA	
Country/Manufacturer	Canada/RPM