

50VA 600 VOLTS TO 120/240 VOLTS SINGLE PHASE CONTROL TRANSFORMER





50VA 600 VOLTS TO 120/240 VOLTS SINGLE PHASE CONTROL TRANSFORMER

\$134.68 CAD


Single Phase Control Transformer with a capacity of 50VA, transforming 600 Volts to 120/240 Volts

SKU: CE50J-K

Categories: Control Transformers

SCHEMATIC/DIAGRAM AND DIMENSION PICTURES





Single Phase Control Transformer with a capacity of 50VA, transforming 600 Volts to 120/240 Volts





50VA 600 VOLTS TO 120/240 VOLTS SINGLE PHASE CONTROL TRANSFORMER





50VA 600 VOLTS TO 120/240 VOLTS SINGLE PHASE CONTROL TRANSFORMER

PRODUCT SPECIFICATIONS

Weight	3 lbs
Phases	1
Connection	1Ph-CT-SD-SD
Primary Voltage	600
Primary Max Current	<u>0.08A</u>
Primary Markings	H1-H2
Primary Terminals	<u>Leads</u>
Secondary Voltage	120/240
Secondary Max Current	<u>0.42A</u>
Secondary Markings	<u>X1-X2-X3-X4</u>
Secondary Terminals	<u>Leads</u>
Primary Taps	N/A
Conductor Material	Copper
Temperatue Rise	80°C
Insuation Class	130°C (Class B)
BIL (Insulation) Level	<u>10kV</u>
Efficiency (@35% Load) %	N/A
Impedance Range	<u>5.0 - 7.0%</u>
Sound (db)	40
Enclosure Type	Type-1 Indoor
Enclosure Size	See Enclosure Chart
Finish/Colour	Semigloss - Black
Standards & Certifications	CSA Certified File No. LR34493, UL Listed File No. E110286, ISO 9001:2015 Registered





50VA 600 VOLTS TO 120/240 VOLTS SINGLE PHASE CONTROL TRANSFORMER

VA	50
Country/Manufacturer	Canada/RPM