

50VA 600 VOLTS TO 120 VOLTS SINGLE PHASE CONTROL TRANSFORMER





50VA 600 VOLTS TO 120 VOLTS SINGLE PHASE CONTROL TRANSFORMER

\$89.02 USD


Single Phase Control Transformer with a capacity of 50VA, transforming 600 Volts to 120 Volts

SKU: CE50J-A

Categories: Control Transformers

SCHEMATIC/DIAGRAM AND DIMENSION PICTURES





Single Phase Control Transformer with a capacity of 50VA, transforming 600 Volts to 120 Volts



50VA 600 VOLTS TO 120 VOLTS SINGLE PHASE CONTROL TRANSFORMER





50VA 600 VOLTS TO 120 VOLTS SINGLE PHASE CONTROL TRANSFORMER

PRODUCT SPECIFICATIONS

Weight	3 lbs
Phases	1
Connection	1Ph-CT-SS-SU
Primary Voltage	600
Primary Max Current	<u>0.08A</u>
Primary Markings	H1-H2
Primary Terminals	Leads
Secondary Voltage	120
Secondary Max Current	<u>0.42A</u>
Secondary Markings	<u>X1-X2</u>
Secondary Terminals	<u>Leads</u>
Primary Taps	N/A
Conductor Material	<u>Copper</u>
Temperatue Rise	80°C
Insuation Class	130°C (Class B)
BIL (Insulation) Level	<u>10kV</u>
Efficiency (@35% Load) %	N/A
Impedance Range	<u>5.0 - 7.0%</u>
Sound (db)	40
Enclosure Type	Type-1 Indoor
Enclosure Size	See Enclosure Chart
Finish/Colour	Semigloss - Black
Standards & Certifications	CSA Certified File No. LR34493, UL Listed File No. E110286, ISO 9001:2015 Registered





50VA 600 VOLTS TO 120 VOLTS SINGLE PHASE CONTROL TRANSFORMER

VA	50
Country/Manufacturer	Canada/RPM