



# RC9J-H/EP

## \$1,656.00 CAD

SKU: ff3826e136d6  
Categories: [Encapsulated Autotransformer](#)

### SCHEMATIC/DIAGRAM AND DIMENSION PICTURES



### PRODUCT SPECIFICATIONS

|        |                   |
|--------|-------------------|
| Weight | 160 lbs           |
| Phases | <a href="#">3</a> |
| kVA    | <a href="#">9</a> |



|                        |                                |
|------------------------|--------------------------------|
| Connection             | <a href="#">3PhA-NT-1</a>      |
| Primary Voltage        | <a href="#">600</a>            |
| Primary Max Current    | <a href="#">8.7A</a>           |
| Primary Markings       | <a href="#">H1-H2-H3</a>       |
| Primary Terminals      | <a href="#">#2-14 AWG</a>      |
| Secondary Voltage      | <a href="#">480</a>            |
| Secondary Max Current  | <a href="#">10.8A</a>          |
| Secondary Markings     | <a href="#">X1-X2-X3</a>       |
| Secondary Terminals    | <a href="#">#2-14 AWG</a>      |
| Primary Taps           | <a href="#">N/A</a>            |
| Conductor Material     | <a href="#">Copper</a>         |
| Insuation Class        | <a href="#">220</a>            |
| BIL (Insulation) Level | <a href="#">10kV</a>           |
| Efficiency             | <a href="#">N/A</a>            |
| Impedance              | <a href="#">0.5 – 1.5%</a>     |
| Sound (db)             | <a href="#">45</a>             |
| Enclosure Type         | <a href="#">NEMA 3R Indoor</a> |
| Enclosure              | <a href="#">E3R-3PEP-1</a>     |