



## RS100H

**\$1,644.00 CAD**

SKU: 632ac6ad8606

Categories: [Motor Starters](#)

### SCHEMATIC/DIAGRAM AND DIMENSION PICTURES



### PRODUCT SPECIFICATIONS

Weight	130 lbs
Phases	<a href="#">3</a>
HP	<a href="#">100</a>
Connection	<a href="#">3PhA-ST-0-3</a>
Primary Voltage	<a href="#">480</a>
Primary Max Current	<a href="#">120.3A</a>
Primary Markings	<a href="#">H1-H2-H3</a>



Primary Terminals	<a href="#">Pads</a>
Secondary Voltage	<a href="#">50/65/80/100%</a>
Secondary Max Current	<a href="#">1154.7A</a>
Secondary Markings	<a href="#">A-B-C-D</a>
Secondary Terminals	<a href="#">Pads</a>
Primary Taps	<a href="#">N/A</a>
Conductor Material	<a href="#">Copper</a>
Temperatue Rise	<a href="#">150°C</a>
Insuation Class	<a href="#">220°C</a>
BIL (Insulation) Level	<a href="#">10kV</a>
Efficiency	<a href="#">N/A</a>
Impedance	<a href="#">N/A</a>
Sound (db)	<a href="#">N/A</a>
Enclosure Type	<a href="#">Core &amp; Coil</a>
Enclosure	<a href="#">N/A</a>
Finish	<a href="#">N/A</a>
Standards & Certifications	<a href="#">CSA Certified File No. LR34493, UL Listed File No. E108255, ISO 9001:2015 Registered</a>