



## RS20H

**\$667.98 USD**

SKU: 0f9712b80313

Categories: [Motor Starters](#)

### SCHEMATIC/DIAGRAM AND DIMENSION PICTURES



### PRODUCT SPECIFICATIONS

Weight	50 lbs
Phases	<a href="#">3</a>
HP	<a href="#">20</a>
Connection	<a href="#">3PhA-ST-0-2</a>
Primary Voltage	<a href="#">480</a>
Primary Max Current	<a href="#">24.1A</a>



<b>Primary Markings</b>	<a href="#">H1-H2-H3</a>
<b>Primary Terminals</b>	<a href="#">Large Scews</a>
<b>Secondary Voltage</b>	<a href="#">65/80/100%</a>
<b>Secondary Max Current</b>	<a href="#">177.6A</a>
<b>Secondary Markings</b>	<a href="#">A-B-C</a>
<b>Secondary Terminals</b>	<a href="#">Large Scews</a>
<b>Primary Taps</b>	<a href="#">N/A</a>
<b>Conductor Material</b>	<a href="#">Copper</a>
<b>Temperatue Rise</b>	<a href="#">115°C</a>
<b>Insuation Class</b>	<a href="#">180°C</a>
<b>BIL (Insulation) Level</b>	<a href="#">10kV</a>
<b>Efficiency</b>	<a href="#">N/A</a>
<b>Impedance</b>	<a href="#">N/A</a>
<b>Sound (db)</b>	<a href="#">N/A</a>
<b>Enclosure Type</b>	<a href="#">Core &amp; Coil</a>
<b>Enclosure</b>	<a href="#">N/A</a>
<b>Finish</b>	<a href="#">N/A</a>
<b>Standards &amp; Certifications</b>	<a href="#">CSA Certified File No. LR34493, UL Listed File No. E108255, ISO 9001:2015 Registered</a>