



**RS500J**

**\$6,153.00 CAD**

SKU: f76fca1480d1

Categories: [Motor Starters](#)

## SCHEMATIC/DIAGRAM AND DIMENSION PICTURES



## PRODUCT SPECIFICATIONS

Weight	550 lbs
Phases	<a href="#">3</a>
HP	<a href="#">500</a>
Connection	<a href="#">3PhA-ST-0-3</a>
Primary Voltage	<a href="#">600</a>
Primary Max Current	<a href="#">481.1A</a>
Primary Markings	<a href="#">H1-H2-H3</a>



Primary Terminals	<a href="#">Pads</a>
Secondary Voltage	<a href="#">50/65/80/100%</a>
Secondary Max Current	<a href="#">5773.5A</a>
Secondary Markings	<a href="#">A-B-C-D</a>
Secondary Terminals	<a href="#">Pads</a>
Primary Taps	<a href="#">N/A</a>
Conductor Material	<a href="#">Copper</a>
Insulation Class	<a href="#">220</a>
BIL (Insulation) Level	<a href="#">10kV</a>
Efficiency	<a href="#">N/A</a>
Impedance	<a href="#">N/A</a>
Sound (db)	<a href="#">N/A</a>
Enclosure Type	<a href="#">N/A</a>
Enclosure	<a href="#">Core &amp; Coil</a>