

OFFICIAL QUOTE

2000KVA 600 VOLTS TO 400 VOLTS THREE PHASE AUTOTRANSFORMER





2000KVA 600 VOLTS TO 400 VOLTS THREE PHASE AUTOTRANSFORMER


\$23,297.73 USD

Three Phase Autotransformer with a capacity of 2000kVA, transforming 600Y Volts to 400Y Volts

SKU: RA2000J-G1

Categories: <u>Autotransformer</u>

SCHEMATIC/DIAGRAM AND DIMENSION PICTURES





Three Phase Autotransformer with a capacity of 2000kVA, transforming 600Y Volts to 400Y Volts



OFFICIAL QUOTE



2000KVA 600 VOLTS TO 400 VOLTS THREE PHASE AUTOTRANSFORMER

PRODUCT SPECIFICATIONS

PRODUCT SPECIFICATIONS	
Weight	4567 lbs
Phases	<u>3</u>
kVA	2000
Connection	3PhA-NT-1
Primary Voltage	600
Primary Max Current	<u>1924.5A</u>
Primary Markings	<u>H1-H2-H3</u>
Primary Terminals	<u>Pads</u>
Secondary Voltage	400
Secondary Max Current	2886.8A
Secondary Markings	<u>X1-X2-X3</u>
Secondary Terminals	<u>Pads</u>
Primary Taps	N/A
Conductor Material	Aluminum
Insulation Class	220°C (Class H)
BIL (Insulation) Level	<u>10kV</u>
Efficiency (@35% Load) %	N/A
Impedance Range	1.0 - 3.0%
Sound (db)	62
Enclosure Type	NEMA 3R Indoor
Enclosure Size	<u>E3R-11</u>
Finish/Colour	Polyester Powder Coat – ANSI/ASA 61 Grey
Standards & Certifications	CSA Certified File No. LR34493, UL Listed File No. E108255, ISO 9001:2015 Registered



OFFICIAL QUOTE

2000KVA 600 VOLTS TO 400 VOLTS THREE PHASE AUTOTRANSFORMER



Country/Manufacturer	Canada/RPM
----------------------	------------