

OFFICIAL QUOTE

500KVA 575 VOLTS TO 240 VOLTS THREE PHASE AUTOTRANSFORMER





500KVA 575 VOLTS TO 240 VOLTS THREE PHASE AUTOTRANSFORMER

\$13,946.80 USD

Three Phase Autotransformer with a capacity of 500kVA, transforming 575Y Volts to 240Y Volts

SKU: RA500J1-C

Categories: Autotransformer

SCHEMATIC/DIAGRAM AND DIMENSION PICTURES





Three Phase Autotransformer with a capacity of 500kVA, transforming 575Y Volts to 240Y Volts



OFFICIAL QUOTE



500KVA 575 VOLTS TO 240 VOLTS THREE PHASE AUTOTRANSFORMER

PRODUCT SPECIFICATIONS

PRODUCT SPECIFICATIONS	
Weight	2088 lbs
Phases	<u>3</u>
kVA	500
Connection	3PhA-NT-1
Primary Voltage	<u>575</u>
Primary Max Current	502A
Primary Markings	H1-H2-H3
Primary Terminals	<u>Pads</u>
Secondary Voltage	240
Secondary Max Current	1202.8A
Secondary Markings	<u>X1-X2-X3</u>
Secondary Terminals	<u>Pads</u>
Primary Taps	N/A
Conductor Material	Aluminum
Insulation Class	220°C (Class H)
BIL (Insulation) Level	<u>10kV</u>
Efficiency (@35% Load) %	N/A
Impedance Range	1.5 - 3.5%
Sound (db)	60
Enclosure Type	NEMA 3R Indoor
Enclosure Size	E3R-9
Finish/Colour	Polyester Powder Coat - ANSI/ASA 61 Grey
Standards & Certifications	CSA Certified File No. LR34493, UL Listed File No. E108255, ISO 9001:2015 Registered



OFFICIAL QUOTE

500KVA 575 VOLTS TO 240 VOLTS THREE PHASE AUTOTRANSFORMER



Country/Manufacturer	Canada/RPM
----------------------	------------