

#### **OFFICIAL QUOTE**

## 300KVA 240 VOLTS TO 120 VOLTS THREE PHASE AUTOTRANSFORMER





# 300KVA 240 VOLTS TO 120 VOLTS THREE PHASE AUTOTRANSFORMER


\$11,364.70 CAD

Three Phase Autotransformer with a capacity of 300kVA, transforming 240Y Volts to 120Y Volts

**SKU:** RA300C-A

**Categories:** Autotransformer

#### SCHEMATIC/DIAGRAM AND DIMENSION PICTURES





Three Phase Autotransformer with a capacity of 300kVA, transforming 240Y Volts to 120Y Volts



### **OFFICIAL QUOTE**





### **PRODUCT SPECIFICATIONS**

Weight	973 lbs
Phases	<u>3</u>
kVA	300
Connection	3PhA-NT-1
Primary Voltage	240
Primary Max Current	721.7A
Primary Markings	<u>H1-H2-H3</u>
Primary Terminals	<u>Pads</u>
Secondary Voltage	120
Secondary Max Current	1443.4A
Secondary Markings	<u>X1-X2-X3</u>
Secondary Terminals	<u>Pads</u>
Primary Taps	N/A
Conductor Material	Aluminum
Insulation Class	220°C (Class H)
BIL (Insulation) Level	<u>10kV</u>
Efficiency (@35% Load) %	N/A
Impedance Range	1.5 - 3.5%
Sound (db)	<u>55</u>
Enclosure Type	NEMA 3R Indoor
Enclosure Size	<u>E3R-8</u>
Finish/Colour	Polyester Powder Coat - ANSI/ASA 61 Grey
Standards & Certifications	CSA Certified File No. LR34493, UL Listed File No. E108255, ISO 9001:2015 Registered



### **OFFICIAL QUOTE**

## 300KVA 240 VOLTS TO 120 VOLTS THREE PHASE AUTOTRANSFORMER



Country/Manufacturer	Canada/RPM
----------------------	------------