

OFFICIAL QUOTE

300KVA 600 VOLTS TO 110 VOLTS THREE PHASE AUTOTRANSFORMER





300KVA 600 VOLTS TO 110 VOLTS THREE PHASE AUTOTRANSFORMER

\$18,050.40 CAD

Three Phase Autotransformer with a capacity of 300kVA, transforming 600Y Volts to 110Y Volts

SKU: RA300J-A2

Categories: Autotransformer

SCHEMATIC/DIAGRAM AND DIMENSION PICTURES





Three Phase Autotransformer with a capacity of 300kVA, transforming 600Y Volts to 110Y Volts



OFFICIAL QUOTE





PRODUCT SPECIFICATIONS

Weight	1711 lbs
Phases	<u>3</u>
kVA	300
Connection	3PhA-NT-1
Primary Voltage	600
Primary Max Current	288.7A
Primary Markings	H1-H2-H3
Primary Terminals	<u>Pads</u>
Secondary Voltage	110
Secondary Max Current	1574.6A
Secondary Markings	<u>X1-X2-X3</u>
Secondary Terminals	<u>Pads</u>
Primary Taps	N/A
Conductor Material	Aluminum
Insulation Class	220°C (Class H)
BIL (Insulation) Level	<u>10kV</u>
Efficiency (@35% Load) %	N/A
Impedance Range	<u>2.5 – 4.5%</u>
Sound (db)	60
Enclosure Type	NEMA 3R Indoor
Enclosure Size	<u>E3R-9</u>
Finish/Colour	Polyester Powder Coat – ANSI/ASA 61 Grey
Standards & Certifications	CSA Certified File No. LR34493, UL Listed File No. E108255, ISO 9001:2015 Registered



OFFICIAL QUOTE

300KVA 600 VOLTS TO 110 VOLTS THREE PHASE AUTOTRANSFORMER



Country/Manufacturer	Canada/RPM
----------------------	------------