

#### **OFFICIAL QUOTE**

### 1000KVA 600 VOLTS TO 347 VOLTS THREE PHASE AUTOTRANSFORMER





### 1000KVA 600 VOLTS TO 347 VOLTS THREE PHASE AUTOTRANSFORMER

\$29,143.60 CAD


Three Phase Autotransformer with a capacity of 1000kVA, transforming 600Y Volts to 347Y Volts

**SKU:** RA1000J-E

**Categories:** Autotransformer

#### **SCHEMATIC/DIAGRAM AND DIMENSION PICTURES**





Three Phase Autotransformer with a capacity of 1000kVA, transforming 600Y Volts to 347Y Volts



#### **OFFICIAL QUOTE**



# 1000KVA 600 VOLTS TO 347 VOLTS THREE PHASE AUTOTRANSFORMER

#### PRODUCT SPECIFICATIONS

PRODUCT SPECIFICATIONS	
Weight	2697 lbs
Phases	<u>3</u>
kVA	1000
Connection	3PhA-NT-1
Primary Voltage	600
Primary Max Current	962.3A
Primary Markings	H1-H2-H3
Primary Terminals	<u>Pads</u>
Secondary Voltage	347
Secondary Max Current	<u>1663.8A</u>
Secondary Markings	<u>X1-X2-X3</u>
Secondary Terminals	<u>Pads</u>
Primary Taps	N/A
Conductor Material	Aluminum
Insulation Class	220°C (Class H)
BIL (Insulation) Level	<u>10kV</u>
Efficiency (@35% Load) %	N/A
Impedance Range	1.5 - 3.5%
Sound (db)	60
Enclosure Type	NEMA 3R Indoor
Enclosure Size	E3R-10
Finish/Colour	Polyester Powder Coat - ANSI/ASA 61 Grey
Standards & Certifications	CSA Certified File No. LR34493, UL Listed File No. E108255, ISO 9001:2015 Registered



#### **OFFICIAL QUOTE**

# 1000KVA 600 VOLTS TO 347 VOLTS THREE PHASE AUTOTRANSFORMER



Country/Manufacturer	Canada/RPM
----------------------	------------