

350VA 600 VOLTS TO 120/240 VOLTS SINGLE PHASE CONTROL TRANSFORMER





### 350VA 600 VOLTS TO 120/240 VOLTS SINGLE PHASE CONTROL TRANSFORMER


### \$274.82 CAD

Single Phase Control Transformer with a capacity of 350VA, transforming 600 Volts to 120/240 Volts

SKU: CE350J-K Categories: <u>Control Transformers</u>

### SCHEMATIC/DIAGRAM AND DIMENSION PICTURES





Single Phase Control Transformer with a capacity of 350VA, transforming 600 Volts to 120/240 Volts



### 350VA 600 VOLTS TO 120/240 VOLTS SINGLE PHASE CONTROL TRANSFORMER





# 

### 350VA 600 VOLTS TO 120/240 VOLTS SINGLE PHASE CONTROL TRANSFORMER

#### **PRODUCT SPECIFICATIONS**

| Weight                     | 12 lbs  |
|----------------------------|---|
| Phases                     | 1   |
| Connection                 | <u>1Ph-CT-SD-SD</u>   |
| Primary Voltage            | <u>600</u>  |
| Primary Max Current        | <u>0.58A</u>  |
| Primary Markings           | <u>H1-H2</u>  |
| Primary Terminals          | <u>Leads</u>  |
| Secondary Voltage          | <u>120/240</u>  |
| Secondary Max Current      | <u>2.92A</u>  |
| Secondary Markings         | <u>X1-X2-X3-X4</u>  |
| Secondary Terminals        | <u>Leads</u>  |
| Primary Taps               | N/A   |
| Conductor Material         | <u>Copper</u>   |
| Temperatue Rise            | <u>80°C</u>   |
| Insuation Class            | <u>130°C (Class B)</u>  |
| BIL (Insulation) Level     | <u>10kV</u>   |
| Efficiency (@35% Load) %   | N/A   |
| Impedance Range            | <u>5.0 – 7.0%</u>   |
| Sound (db)                 | <u>40</u>   |
| Enclosure Type             | <u>Type-1 Indoor</u>  |
| Enclosure Size             | See Enclosure Chart   |
| Finish/Colour              | <u>Semigloss – Black</u>  |
| Standards & Certifications | <u>CSA Certified File No. LR34493, UL Listed File No. E110286, ISO 9001:2015</u><br><u>Registered</u> |

The quote is valid 30 days from 17 June 2025. The price does not include: "Special Features", freight and possible taxes. Disclosing this information to the third party or other supplier may lead to the cancellation of this quote. All other requests please email to sales@transformersource.ca. Printed: September-16-2024.



## 

### 350VA 600 VOLTS TO 120/240 VOLTS SINGLE PHASE CONTROL TRANSFORMER

| VA                   | 350        | - |
|----------------------|------------|---|
| Country/Manufacturer | Canada/RPM |   |