

OFFICIAL QUOTE

1000KVA 600 VOLTS TO 277 VOLTS THREE PHASE AUTOTRANSFORMER





1000KVA 600 VOLTS TO 277 VOLTS THREE PHASE AUTOTRANSFORMER


\$25,771.10 CAD

Three Phase Autotransformer with a capacity of 1000kVA, transforming 600Y Volts to 277Y Volts

SKU: RA1000J-D

Categories: <u>Autotransformer</u>

SCHEMATIC/DIAGRAM AND DIMENSION PICTURES





Three Phase Autotransformer with a capacity of 1000kVA, transforming 600Y Volts to 277Y Volts



OFFICIAL QUOTE



1000KVA 600 VOLTS TO 277 VOLTS THREE PHASE AUTOTRANSFORMER

PRODUCT SPECIFICATIONS

PRODUCT SPECIFICATIONS	
Weight	3571 lbs
Phases	<u>3</u>
kVA	1000
Connection	3PhA-NT-1
Primary Voltage	600
Primary Max Current	962.3A
Primary Markings	<u>H1-H2-H3</u>
Primary Terminals	<u>Pads</u>
Secondary Voltage	277
Secondary Max Current	2084.3A
Secondary Markings	<u>X1-X2-X3</u>
Secondary Terminals	<u>Pads</u>
Primary Taps	N/A
Conductor Material	Aluminum
Insulation Class	220°C (Class H)
BIL (Insulation) Level	<u>10kV</u>
Efficiency (@35% Load) %	N/A
Impedance Range	1.5 - 3.5%
Sound (db)	62
Enclosure Type	NEMA 3R Indoor
Enclosure Size	<u>E3R-11</u>
Finish/Colour	Polyester Powder Coat - ANSI/ASA 61 Grey
Standards & Certifications	CSA Certified File No. LR34493, UL Listed File No. E108255, ISO 9001:2015 Registered



OFFICIAL QUOTE

1000KVA 600 VOLTS TO 277 VOLTS THREE PHASE AUTOTRANSFORMER



Country/Manufacturer	<u>Canada/RPM</u>
----------------------	-------------------