

OFFICIAL QUOTE

500VA 480 VOLTS TO 120 VOLTS SINGLE PHASE CONTROL TRANSFORMER





500VA 480 VOLTS TO 120 VOLTS SINGLE PHASE CONTROL TRANSFORMER

\$252.98 CAD


Single Phase Control Transformer with a capacity of 500VA, transforming 480 Volts to 120 Volts

SKU: CE500H-A

Categories: Control Transformers

SCHEMATIC/DIAGRAM AND DIMENSION PICTURES





Single Phase Control Transformer with a capacity of 500VA, transforming 480 Volts to 120 Volts



OFFICIAL QUOTE



500VA 480 VOLTS TO 120 VOLTS SINGLE PHASE CONTROL TRANSFORMER

PRODUCT SPECIFICATIONS

PRODUCT SPECIFICATIONS	
Weight	5 lbs
Phases	1
Connection	1Ph-CT-SS-SU
Primary Voltage	480
Primary Max Current	<u>1.04A</u>
Primary Markings	<u>H1-H2</u>
Primary Terminals	Leads
Secondary Voltage	120
Secondary Max Current	4.17A
Secondary Markings	<u>X1-X2</u>
Secondary Terminals	Leads
Primary Taps	N/A
Conductor Material	Copper
Temperatue Rise	<u>115°C</u>
Insuation Class	180°C (Class F)
BIL (Insulation) Level	<u>10kV</u>
Efficiency (@35% Load) %	N/A
Impedance Range	<u>5.0 - 7.0%</u>
Sound (db)	40
Enclosure Type	Type-1 Indoor
Enclosure Size	See Enclosure Chart
Finish/Colour	Semigloss - Black
Standards & Certifications	CSA Certified File No. LR34493, UL Listed File No. E110286, ISO 9001:2015 Registered



OFFICIAL QUOTE

500VA 480 VOLTS TO 120 VOLTS SINGLE PHASE CONTROL TRANSFORMER

VA	
Country/Manufacturer	Canada/RPM