



2000KVA 380 VOLTS TO 240 VOLTS THREE PHASE AUTOTRANSFORMER

\$25,750.09 USD

Three Phase Autotransformer with a capacity of 2000kVA, transforming 380Y Volts to 240Y Volts

SKU: RA2000F-C

Categories: [Autotransformer](#)

SCHEMATIC/DIAGRAM AND DIMENSION PICTURES



Three Phase Autotransformer with a capacity of 2000kVA, transforming 380Y Volts to 240Y Volts



PRODUCT SPECIFICATIONS

Weight	5124 lbs
Phases	3
kVA	2000
Connection	3PhA-NT-1
Primary Voltage	380
Primary Max Current	3038.7A
Primary Markings	H1-H2-H3
Primary Terminals	Pads
Secondary Voltage	240
Secondary Max Current	4811.3A
Secondary Markings	X1-X2-X3
Secondary Terminals	Pads
Primary Taps	N/A
Conductor Material	Aluminum
Insulation Class	220°C (Class H)
BIL (Insulation) Level	10kV
Efficiency (@35% Load) %	N/A
Impedance Range	1.0 – 3.0%
Sound (db)	64
Enclosure Type	NEMA 3R Indoor
Enclosure Size	E3R-11
Finish/Colour	Polyester Powder Coat – ANSI/ASA 61 Grey
Standards & Certifications	CSA Certified File No. LR34493, UL Listed File No. E108255, ISO 9001:2015 Registered



OFFICIAL QUOTE

2000KVA 380 VOLTS TO 240 VOLTS
THREE PHASE AUTOTRANSFORMER



Country/Manufacturer	Canada/RPM
----------------------	----------------------------