

OFFICIAL QUOTE

2000KVA 380 VOLTS TO 240 VOLTS THREE PHASE AUTOTRANSFORMER





2000KVA 380 VOLTS TO 240 VOLTS THREE PHASE AUTOTRANSFORMER


\$35,274.10 CAD

Three Phase Autotransformer with a capacity of 2000kVA, transforming 380Y Volts to 240Y Volts

SKU: RA2000F-C

Categories: <u>Autotransformer</u>

SCHEMATIC/DIAGRAM AND DIMENSION PICTURES





Three Phase Autotransformer with a capacity of 2000kVA, transforming 380Y Volts to 240Y Volts



OFFICIAL QUOTE



2000KVA 380 VOLTS TO 240 VOLTS THREE PHASE AUTOTRANSFORMER

PRODUCT SPECIFICATIONS

PRODUCT SPECIFICATIONS	
Weight	5124 lbs
Phases	<u>3</u>
kVA	2000
Connection	3PhA-NT-1
Primary Voltage	380
Primary Max Current	3038.7A
Primary Markings	<u>H1-H2-H3</u>
Primary Terminals	<u>Pads</u>
Secondary Voltage	240
Secondary Max Current	4811.3A
Secondary Markings	<u>X1-X2-X3</u>
Secondary Terminals	<u>Pads</u>
Primary Taps	N/A
Conductor Material	Aluminum
Insulation Class	220°C (Class H)
BIL (Insulation) Level	<u>10kV</u>
Efficiency (@35% Load) %	N/A
Impedance Range	1.0 - 3.0%
Sound (db)	64
Enclosure Type	NEMA 3R Indoor
Enclosure Size	E3R-11
Finish/Colour	Polyester Powder Coat - ANSI/ASA 61 Grey
Standards & Certifications	CSA Certified File No. LR34493, UL Listed File No. E108255, ISO 9001:2015 Registered



OFFICIAL QUOTE

2000KVA 380 VOLTS TO 240 VOLTS THREE PHASE AUTOTRANSFORMER



Country/Manufacturer	Canada/RPM
----------------------	------------