



## 45KVA 347 VOLTS TO 416 VOLTS THREE PHASE AUTOTRANSFORMER

**\$2,351.10 CAD**

Three Phase Autotransformer with a capacity of 45kVA, transforming 347Y Volts to 416Y Volts

SKU: RC45E-G

Categories: [Autotransformer](#)

### SCHEMATIC/DIAGRAM AND DIMENSION PICTURES



Three Phase Autotransformer with a capacity of 45kVA, transforming 347Y Volts to 416Y Volts



## PRODUCT SPECIFICATIONS

|                            |  |
|----------------------------|--|
| Weight                     | 55 lbs   |
| Phases                     | <a href="#">3</a>  |
| kVA                        | <a href="#">45</a>   |
| Connection                 | <a href="#">3PhA-NT-1</a>  |
| Primary Voltage            | <a href="#">347</a>  |
| Primary Max Current        | <a href="#">74.9A</a>  |
| Primary Markings           | <a href="#">X1-X2-X3</a>   |
| Primary Terminals          | <a href="#">#2/0-6 AWG</a>   |
| Secondary Voltage          | <a href="#">416</a>  |
| Secondary Max Current      | <a href="#">62.5A</a>  |
| Secondary Markings         | <a href="#">H1-H2-H3</a>   |
| Secondary Terminals        | <a href="#">#2-14 AWG</a>  |
| Primary Taps               | <a href="#">N/A</a>  |
| Conductor Material         | <a href="#">Copper</a>   |
| Insulation Class           | <a href="#">220°C (Class H)</a>  |
| BIL (Insulation) Level     | <a href="#">10kV</a>   |
| Efficiency (@35% Load) %   | <a href="#">N/A</a>  |
| Impedance Range            | <a href="#">0.5 – 1.5%</a>   |
| Sound (db)                 | <a href="#">40</a>   |
| Enclosure Type             | <a href="#">NEMA 1</a>   |
| Enclosure Size             | <a href="#">E1-3</a>   |
| Finish/Colour              | <a href="#">Polyester Powder Coat – ANSI/ASA 61 Grey</a>   |
| Standards & Certifications | <a href="#">CSA Certified File No. LR34493, UL Listed File No. E108255, ISO 9001:2015 Registered</a> |



OFFICIAL QUOTE

45KVA 347 VOLTS TO 416 VOLTS  
THREE PHASE AUTOTRANSFORMER



|                      |                            |
|----------------------|----------------------------|
| Country/Manufacturer | <a href="#">Canada/RPM</a> |
|----------------------|----------------------------|