

#### **OFFICIAL QUOTE**

### 600KVA 400 VOLTS TO 416 VOLTS THREE PHASE AUTOTRANSFORMER





### 600KVA 400 VOLTS TO 416 VOLTS THREE PHASE AUTOTRANSFORMER


\$4,500.00 CAD

Three Phase Autotransformer with a capacity of 600kVA, transforming 400Y Volts to 416Y Volts

**SKU: RA600G1-G** 

**Categories:** Autotransformer

#### **SCHEMATIC/DIAGRAM AND DIMENSION PICTURES**





Three Phase Autotransformer with a capacity of 600kVA, transforming 400Y Volts to 416Y Volts



#### **OFFICIAL QUOTE**



# 600KVA 400 VOLTS TO 416 VOLTS THREE PHASE AUTOTRANSFORMER

#### **PRODUCT SPECIFICATIONS**

PRODUCT SPECIFICATIONS	
Weight	149 lbs
Phases	<u>3</u>
kVA	600
Connection	3PhA-NT-1
Primary Voltage	400
Primary Max Current	866A
Primary Markings	<u>X1-X2-X3</u>
Primary Terminals	Pads
Secondary Voltage	416
Secondary Max Current	832.7A
Secondary Markings	<u>H1-H2-H3</u>
Secondary Terminals	<u>Pads</u>
Primary Taps	N/A
Conductor Material	Aluminum
Insulation Class	220°C (Class H)
BIL (Insulation) Level	<u>10kV</u>
Efficiency (@35% Load) %	N/A
Impedance Range	0.5 - 1.5%
Sound (db)	<u>45</u>
Enclosure Type	NEMA 3R Indoor
Enclosure Size	<u>E3R-6</u>
Finish/Colour	Polyester Powder Coat - ANSI/ASA 61 Grey
Standards & Certifications	CSA Certified File No. LR34493, UL Listed File No. E108255, ISO 9001:2015 Registered



#### **OFFICIAL QUOTE**

# 600KVA 400 VOLTS TO 416 VOLTS THREE PHASE AUTOTRANSFORMER



Country/Manufacturer	Canada/RPM
----------------------	------------