

OFFICIAL QUOTE

600KVA 600 VOLTS TO 380 VOLTS THREE PHASE AUTOTRANSFORMER





600KVA 600 VOLTS TO 380 VOLTS THREE PHASE AUTOTRANSFORMER


\$17,321.50 CAD

Three Phase Autotransformer with a capacity of 600kVA, transforming 600Y Volts to 380Y Volts

SKU: RA600J-F

Categories: Autotransformer

SCHEMATIC/DIAGRAM AND DIMENSION PICTURES





Three Phase Autotransformer with a capacity of 600kVA, transforming 600Y Volts to 380Y Volts



OFFICIAL QUOTE



600KVA 600 VOLTS TO 380 VOLTS THREE PHASE AUTOTRANSFORMER

PRODUCT SPECIFICATIONS

PRODUCT SPECIFICATIONS	
Weight	1512 lbs
Phases	<u>3</u>
kVA	600
Connection	3PhA-NT-1
Primary Voltage	600
Primary Max Current	577.4A
Primary Markings	H1-H2-H3
Primary Terminals	<u>Pads</u>
Secondary Voltage	380
Secondary Max Current	911.6A
Secondary Markings	<u>X1-X2-X3</u>
Secondary Terminals	<u>Pads</u>
Primary Taps	N/A
Conductor Material	Aluminum
Insulation Class	220°C (Class H)
BIL (Insulation) Level	<u>10kV</u>
Efficiency (@35% Load) %	N/A
Impedance Range	1.0 - 3.0%
Sound (db)	60
Enclosure Type	NEMA 3R Indoor
Enclosure Size	E3R-9
Finish/Colour	Polyester Powder Coat - ANSI/ASA 61 Grey
Standards & Certifications	CSA Certified File No. LR34493, UL Listed File No. E108255, ISO 9001:2015 Registered



OFFICIAL QUOTE

600KVA 600 VOLTS TO 380 VOLTS THREE PHASE AUTOTRANSFORMER



Country/Manufacturer	Canada/RPM
----------------------	------------