



50HP 600 VOLTS THREE PHASE MOTOR STARTER

\$910.31 USD

Three Phase Motor Starter with a capacity of
50HP, suitable for 600 Volt Systems

SKU: RS50J

Categories: [Motor Starting Autotransformers](#)

SCHEMATIC/DIAGRAM AND DIMENSION PICTURES



Three Phase Motor Starter with a capacity of 50HP, suitable for 600 Volt Systems



PRODUCT SPECIFICATIONS

| | |
|----------------------------|--|
| Weight | 90 lbs |
| Phases | 3 |
| Connection | 3PhA-ST-0-3 |
| Primary Voltage | 600 |
| Primary Max Current | N/A |
| Primary Markings | H1-H2-H3 |
| Primary Terminals | Pads |
| Secondary Voltage | 65/80/100% |
| Secondary Max Current | N/A |
| Secondary Markings | A-B-C-D |
| Secondary Terminals | Pads |
| Primary Taps | N/A |
| Conductor Material | Copper |
| Temperatue Rise | 150°C |
| Insuation Class | 220°C (Class H) |
| BIL (Insulation) Level | 10kV |
| Efficiency (@35% Load) % | N/A |
| Impedance Range | N/A |
| Sound (db) | N/A |
| Enclosure Type | Core & Coil |
| Enclosure Size | N/A (Core & Coil) |
| Finish/Colour | N/A |
| Standards & Certifications | CSA Certified File No. LR34493, UL Listed File No. E108255, ISO 9001:2015 Registered |



OFFICIAL QUOTE
50HP 600 VOLTS THREE PHASE
MOTOR STARTER



| | |
|----------------------|----------------------------|
| HP | 50 |
| Country/Manufacturer | Canada/RPM |