


OFFICIAL QUOTE

30KVA 380 VOLTS TO 110 VOLTS THREE PHASE AUTOTRANSFORMER





30KVA 380 VOLTS TO 110 VOLTS THREE PHASE AUTOTRANSFORMER


\$3,357.90 CAD


Three Phase Autotransformer with a capacity of 30kVA, transforming 380Y Volts to 110Y Volts

SKU: RC30F-A2

Categories: Autotransformer

SCHEMATIC/DIAGRAM AND DIMENSION PICTURES





Three Phase Autotransformer with a capacity of 30kVA, transforming 380Y Volts to 110Y Volts



OFFICIAL QUOTE



30KVA 380 VOLTS TO 110 VOLTS THREE PHASE AUTOTRANSFORMER

PRODUCT SPECIFICATIONS

PRODUCT SPECIFICATIONS	
Weight	182 lbs
Phases	<u>3</u>
kVA	30
Connection	3PhA-NT-1
Primary Voltage	380
Primary Max Current	45.6A
Primary Markings	<u>H1-H2-H3</u>
Primary Terminals	#2-14 AWG
Secondary Voltage	110
Secondary Max Current	<u>157.5A</u>
Secondary Markings	<u>X1-X2-X3</u>
Secondary Terminals	300MCM-6
Primary Taps	N/A
Conductor Material	Copper
Insulation Class	220°C (Class H)
BIL (Insulation) Level	<u>10kV</u>
Efficiency (@35% Load) %	N/A
Impedance Range	<u>2.5 – 4.5%</u>
Sound (db)	45
Enclosure Type	NEMA 3R Indoor
Enclosure Size	<u>E3R-6</u>
Finish/Colour	Polyester Powder Coat - ANSI/ASA 61 Grey
Standards & Certifications	CSA Certified File No. LR34493, UL Listed File No. E108255, ISO 9001:2015 Registered



OFFICIAL QUOTE

30KVA 380 VOLTS TO 110 VOLTS THREE PHASE AUTOTRANSFORMER



Country/Manufacturer	Canada/RPM
----------------------	------------