

OFFICIAL QUOTE

30KVA 400 VOLTS TO 115 VOLTS THREE PHASE AUTOTRANSFORMER





30KVA 400 VOLTS TO 115 VOLTS THREE PHASE AUTOTRANSFORMER

\$2,325.18 USD

Three Phase Autotransformer with a capacity of 30kVA, transforming 400Y Volts to 115Y Volts

SKU: RA30G1-A1

Categories: Autotransformer

SCHEMATIC/DIAGRAM AND DIMENSION PICTURES






Three Phase Autotransformer with a capacity of 30kVA, transforming 400Y Volts to 115Y Volts



OFFICIAL QUOTE





PRODUCT SPECIFICATIONS

Weight	137 lbs
Phases	3
kVA	30
Connection	3PhA-NT-1
Primary Voltage	400
Primary Max Current	43.3A
Primary Markings	H1-H2-H3
Primary Terminals	#2-14 AWG
Secondary Voltage	115
Secondary Max Current	150.6A
Secondary Markings	<u>X1-X2-X3</u>
Secondary Terminals	<u>300MCM-6</u>
Primary Taps	N/A
Conductor Material	<u>Aluminum</u>
Insulation Class	220°C (Class H)
BIL (Insulation) Level	<u>10kV</u>
Efficiency (@35% Load) %	N/A
Impedance Range	<u>2.5 - 4.5%</u>
Sound (db)	45
Enclosure Type	NEMA 3R Indoor
Enclosure Size	<u>E3R-6</u>
Finish/Colour	Polyester Powder Coat – ANSI/ASA 61 Grey
Standards & Certifications	CSA Certified File No. LR34493, UL Listed File No. E108255, ISO 9001:2015 Registered



OFFICIAL QUOTE

30KVA 400 VOLTS TO 115 VOLTS THREE PHASE AUTOTRANSFORMER



Country/Manufacturer	Canada/RPM
----------------------	------------