



## 112KVA 200 VOLTS TO 240 VOLTS THREE PHASE AUTOTRANSFORMER

**\$2,905.10 CAD**

Three Phase Autotransformer with a capacity of 112.5kVA, transforming 200Y Volts to 240Y Volts

**SKU:** RC112B1-C

**Categories:** [Autotransformer](#)

### SCHEMATIC/DIAGRAM AND DIMENSION PICTURES



Three Phase Autotransformer with a capacity of 112.5kVA, transforming 200Y Volts to 240Y Volts



## PRODUCT SPECIFICATIONS

|                            |  |
|----------------------------|--|
| Weight                     | 157 lbs  |
| Phases                     | <a href="#">3</a>  |
| kVA                        | <a href="#">112.5</a>  |
| Connection                 | <a href="#">3PhA-NT-1</a>  |
| Primary Voltage            | <a href="#">200</a>  |
| Primary Max Current        | <a href="#">324.8A</a>   |
| Primary Markings           | <a href="#">X1-X2-X3</a>   |
| Primary Terminals          | <a href="#">Pads</a>   |
| Secondary Voltage          | <a href="#">240</a>  |
| Secondary Max Current      | <a href="#">270.6A</a>   |
| Secondary Markings         | <a href="#">H1-H2-H3</a>   |
| Secondary Terminals        | <a href="#">600MCM-2</a>   |
| Primary Taps               | <a href="#">N/A</a>  |
| Conductor Material         | <a href="#">Copper</a>   |
| Insulation Class           | <a href="#">220°C (Class H)</a>  |
| BIL (Insulation) Level     | <a href="#">10kV</a>   |
| Efficiency (@35% Load) %   | <a href="#">N/A</a>  |
| Impedance Range            | <a href="#">0.5 – 1.5%</a>   |
| Sound (db)                 | <a href="#">45</a>   |
| Enclosure Type             | <a href="#">NEMA 3R Indoor</a>   |
| Enclosure Size             | <a href="#">E3R-5</a>  |
| Finish/Colour              | <a href="#">Polyester Powder Coat – ANSI/ASA 61 Grey</a>   |
| Standards & Certifications | <a href="#">CSA Certified File No. LR34493, UL Listed File No. E108255, ISO 9001:2015 Registered</a> |



OFFICIAL QUOTE

112KVA 200 VOLTS TO 240 VOLTS  
THREE PHASE AUTOTRANSFORMER



|                      |                            |
|----------------------|----------------------------|
| Country/Manufacturer | <a href="#">Canada/RPM</a> |
|----------------------|----------------------------|