



2000VA 347 VOLTS TO 120/240 VOLTS SINGLE PHASE CONTROL TRANSFORMER

\$733.46 CAD



Single Phase Control Transformer with a capacity of 2000VA, transforming 347 Volts to 120/240 Volts

SKU: CE2000E-K

Categories: [Control Transformers](#)

SCHEMATIC/DIAGRAM AND DIMENSION PICTURES

VA Rating	Overall Dimensions (inches)				Mounting Dimensions (inches)			
	A	B	C	D	E	F	G	H
25	3	6	3.5	1.375	4.375			
50	3	6	3.5	1.375	4.375			
100	3	6	3.5	1.375	4.375			
150	3.5	6.658	3.13	3.25	5			
200	3.5	6.658	3.13	3.25	5			
250	3.5	6.658	3.13	3.25	5			
350	4.125	6.5	3.75	3.75	7.875			
500	4.875	7	4.38	4.5	5.5			
750	4.875	7	4.38	4.5	5.5			
1000	4.875	7	4.38	4.5	5.5			
1500	5.625	9	5.63	5	7.25			
2000	6.875	9.25	6.25	6	8			
3000	6.875	9.25	6.25	6	8			
5000	8	10.5	9.5	6	9			



Single Phase Control Transformer with a capacity of 2000VA, transforming 347 Volts to 120/240 Volts



PRODUCT SPECIFICATIONS

Weight	50 lbs
Phases	1
Connection	1Ph-CT-SD-SD
Primary Voltage	347
Primary Max Current	5.76A
Primary Markings	H1-H2
Primary Terminals	Leads
Secondary Voltage	120/240
Secondary Max Current	16.67A
Secondary Markings	X1-X2-X3-X4
Secondary Terminals	Leads
Primary Taps	N/A
Conductor Material	Copper
Temperature Rise	115°C
Insulation Class	180°C (Class F)
BIL (Insulation) Level	10kV
Efficiency (@35% Load) %	N/A
Impedance Range	5.0 – 7.0%
Sound (db)	40
Enclosure Type	Type-1 Indoor
Enclosure Size	See Enclosure Chart
Finish/Colour	Semigloss – Black
Standards & Certifications	CSA Certified File No. LR34493, UL Listed File No. E110286, ISO 9001:2015 Registered



OFFICIAL QUOTE

2000VA 347 VOLTS TO 120/240
VOLTS SINGLE PHASE CONTROL
TRANSFORMER



VA	
Country/Manufacturer	Canada/RPM