

OFFICIAL QUOTE

2000VA 600 VOLTS TO 240/480 VOLTS SINGLE PHASE CONTROL TRANSFORMER





2000VA 600 VOLTS TO 240/480 VOLTS SINGLE PHASE CONTROL TRANSFORMER

\$733.46 CAD


Single Phase Control Transformer with a capacity of 2000VA, transforming 600 Volts to 240/480 Volts

SKU: CE2000J-L

Categories: Control Transformers

SCHEMATIC/DIAGRAM AND DIMENSION PICTURES





Single Phase Control Transformer with a capacity of 2000VA, transforming 600 Volts to 240/480 Volts



OFFICIAL QUOTE



2000VA 600 VOLTS TO 240/480 VOLTS SINGLE PHASE CONTROL TRANSFORMER

PRODUCT SPECIFICATIONS

Weight	50 lbs
Phases	1
Connection	1Ph-CT-SD-SD
Primary Voltage	600
Primary Max Current	3.33A
Primary Markings	<u>H1-H2</u>
Primary Terminals	<u>Leads</u>
Secondary Voltage	240/480
Secondary Max Current	8.33A
Secondary Markings	<u>X1-X2-X3-X4</u>
Secondary Terminals	<u>Leads</u>
Primary Taps	N/A
Conductor Material	Copper
Temperatue Rise	115°C
Insuation Class	180°C (Class F)
BIL (Insulation) Level	10kV
Efficiency (@35% Load) %	N/A
Impedance Range	<u>5.0 - 7.0%</u>
Sound (db)	40
Enclosure Type	Type-1 Indoor
Enclosure Size	See Enclosure Chart
Standards & Certifications	CSA Certified File No. LR34493, UL Listed File No. E110286, ISO 9001:2015 Registered
VA	



OFFICIAL QUOTE

2000VA 600 VOLTS TO 240/480 VOLTS SINGLE PHASE CONTROL TRANSFORMER

Country/Manufacturer	<u>Canada/RPM</u>