

OFFICIAL QUOTE

1000VA 600 VOLTS TO 120/240 VOLTS SINGLE PHASE CONTROL TRANSFORMER





1000VA 600 VOLTS TO 120/240 VOLTS SINGLE PHASE CONTROL TRANSFORMER

\$518.70 CAD


Single Phase Control Transformer with a capacity of 1000VA, transforming 600 Volts to 120/240 Volts

SKU: CE1000J-K

Categories: Control Transformers

SCHEMATIC/DIAGRAM AND DIMENSION PICTURES





Single Phase Control Transformer with a capacity of 1000VA, transforming 600 Volts to 120/240 Volts



OFFICIAL QUOTE



1000VA 600 VOLTS TO 120/240 VOLTS SINGLE PHASE CONTROL TRANSFORMER

PRODUCT SPECIFICATIONS

PRODUCT SPECIFICATIONS	
Weight	23 lbs
Phases	1
Connection	1Ph-CT-SD-SD
Primary Voltage	600
Primary Max Current	1.67A
Primary Markings	<u>H1-H2</u>
Primary Terminals	<u>Leads</u>
Secondary Voltage	120/240
Secondary Max Current	8.33A
Secondary Markings	<u>X1-X2-X3-X4</u>
Secondary Terminals	<u>Leads</u>
Primary Taps	N/A
Conductor Material	<u>Copper</u>
Temperatue Rise	<u>115°C</u>
Insuation Class	180°C (Class F)
BIL (Insulation) Level	10kV
Efficiency (@35% Load) %	N/A
Impedance Range	<u>5.0 - 7.0%</u>
Sound (db)	40
Enclosure Type	Type-1 Indoor
Enclosure Size	See Enclosure Chart
Finish/Colour	Semigloss - Black
Standards & Certifications	CSA Certified File No. LR34493, UL Listed File No. E110286, ISO 9001:2015 Registered



OFFICIAL QUOTE



1000VA 600 VOLTS TO 120/240 VOLTS SINGLE PHASE CONTROL TRANSFORMER

VA	1000
Country/Manufacturer	Canada/RPM