

OFFICIAL QUOTE

9KVA 120 VOLTS TO 400 VOLTS THREE PHASE AUTOTRANSFORMER





9KVA 120 VOLTS TO 400 VOLTS THREE PHASE AUTOTRANSFORMER

\$2,103.80 CAD

Three Phase Autotransformer with a capacity of 9kVA, transforming 120Y Volts to 400Y Volts

SKU: RC9A-G1 Categories: <u>Autotransformer</u>

SCHEMATIC/DIAGRAM AND DIMENSION PICTURES





Three Phase Autotransformer with a capacity of 9kVA, transforming 120Y Volts to 400Y Volts



OFFICIAL QUOTE

9KVA 120 VOLTS TO 400 VOLTS THREE PHASE AUTOTRANSFORMER



PRODUCT SPECIFICATIONS

Weight	45 lbs
Phases	<u>3</u>
kVA	<u>9</u>
Connection	<u>3PhA-NT-1</u>
Primary Voltage	120
Primary Max Current	<u>43.3A</u>
Primary Markings	<u>X1-X2-X3</u>
Primary Terminals	<u>#2-14 AWG</u>
Secondary Voltage	<u>400</u>
Secondary Max Current	<u>13A</u>
Secondary Markings	<u>H1-H2-H3</u>
Secondary Terminals	Terminal Blocks
Primary Taps	N/A
Conductor Material	<u>Copper</u>
Insulation Class	220°C (Class H)
BIL (Insulation) Level	<u>10kV</u>
Efficiency (@35% Load) %	<u>N/A</u>
Impedance Range	<u>2.5 - 4.5%</u>
Sound (db)	<u>40</u>
Enclosure Type	NEMA 1
Enclosure Size	<u>E1-3</u>
Finish/Colour	Polyester Powder Coat – ANSI/ASA 61 Grey
Standards & Certifications	CSA Certified File No. LR34493, UL Listed File No. E108255, ISO 9001:2015 Registered



OFFICIAL QUOTE

9KVA 120 VOLTS TO 400 VOLTS THREE PHASE AUTOTRANSFORMER



Country/Manufacturer

Canada/RPM