



6KVA 347 VOLTS TO 600 VOLTS THREE PHASE AUTOTRANSFORMER

\$1,527.90 CAD

Three Phase Autotransformer with a capacity of 6kVA, transforming 347Y Volts to 600Y Volts

SKU: RC6E-J

Categories: [Autotransformer](#)

SCHEMATIC/DIAGRAM AND DIMENSION PICTURES



Three Phase Autotransformer with a capacity of 6kVA, transforming 347Y Volts to 600Y Volts



PRODUCT SPECIFICATIONS

| | |
|----------------------------|--|
| Weight | 20 lbs |
| Phases | 3 |
| kVA | 6 |
| Connection | 3PhA-NT-1 |
| Primary Voltage | 347 |
| Primary Max Current | 10A |
| Primary Markings | X1-X2-X3 |
| Primary Terminals | Terminal Blocks |
| Secondary Voltage | 600 |
| Secondary Max Current | 5.8A |
| Secondary Markings | H1-H2-H3 |
| Secondary Terminals | Terminal Blocks |
| Primary Taps | N/A |
| Conductor Material | Copper |
| Insulation Class | 180°C (Class F) |
| BIL (Insulation) Level | 10kV |
| Efficiency (@35% Load) % | N/A |
| Impedance Range | 1.5 – 3.5% |
| Sound (db) | 40 |
| Enclosure Type | NEMA 1 |
| Enclosure Size | E1-1 |
| Finish/Colour | Polyester Powder Coat – ANSI/ASA 61 Grey |
| Standards & Certifications | CSA Certified File No. LR34493, UL Listed File No. E108255, ISO 9001:2015 Registered |



OFFICIAL QUOTE
6KVA 347 VOLTS TO 600 VOLTS
THREE PHASE AUTOTRANSFORMER



| | |
|----------------------|----------------------------|
| Country/Manufacturer | Canada/RPM |
|----------------------|----------------------------|